

METHOD AND DEVICE FOR CARRYING OUT SIMPLEX DATA TRANSMISSION

5 Cross-Reference to Related Application:

This application is a continuation of copending International Application No. PCT/DE00/01660, filed May 24, 2000, which designated the United States.

10 Background of the Invention:

Field of the Invention:

15 The invention relates to a method for carrying out simplex data transmission of a data message modulated onto a carrier frequency, in particular, for simplex radio transmission in a radio access control system, and a device to carry out the method.

20 In recent years, electronic access control systems have undergone a surprisingly rapid and widespread distribution in various areas. The functionality of such systems is being continuously extended and, concurrently therewith, the requirements for immunity to interference of the transmission have increased. Thus, in the automotive industry, conventional radio-controlled locking systems, which initially
25 had the importance of a convenience function only (regarded by many car drivers as superfluous), have since become complex

systems, through which not only is access gained to the interior of the vehicle, but through which vehicle functions are also controlled. In modern systems, the transfer of an access code via radio carries out user authentication. For the future, it is proposed to transmit user-specific data, which are required in order to control specific functions, along with the access code. Even taking into account a resulting increase in the scope of the corresponding data messages and the time limits imposed by the specifications of the automobile manufacturers on the total transmission process, the bit rates are relatively low, and simple modulation methods (e.g., OOK = On-Off Keying or FSK = Frequency Shift Keying) and of course, for reasons of cost and space, the simplest possible transmitter and receiver structures are used.

Along with automotive systems, building engineering systems represent a further main focal point for the use of radio access control systems. In addition to garage door controls, which have been in use for some time, access control systems in company offices and public buildings are being increasingly used.

A fundamental problem in the further distribution of radio access control systems is that the frequency band in which these systems have to operate (in Europe the ISM band from

433.05 to 434.79 MHz) is used not only by the rapidly increasing number of such systems, but also by intruder alarm systems, telemetry paths, medical equipment, radio remote controls for model cars, radio telephony links, and crane controls. In individual countries, further users must also be considered, e.g., repeater stations in the United Kingdom. In such a context, it must be borne in mind that radio access control systems, in view of the short required range and in the interest of long battery life, operate with very low transmission powers in the μW range. In view of these circumstances, it is not surprising that interference, and, under unfavorable conditions, even total outage, occur with increasing frequency in radio access control systems.

One way of increasing reliability is to provide redundant transmission paths that operate in a different manner, e.g., an infrared path. However, additional transmitters and receivers that are based on totally different principles and that cannot, therefore, be integrated in any way into the main system are required for such a purpose. As a result, there is an increase in the cost outlay and also in the space requirement. The use of more elaborate coding methods and the use of specific narrowband transmission paths normally result in a substantial increase in cost. The use, for example, of error correction mechanisms existing in mobile radiotelephony, which are based on the artificial addition of redundancy to

the data message to increase transmission reliability,
similarly incurs relatively high hardware and software cost
and, similarly, for reasons of cost, is, therefore, unsuitable
for low-cost radio access control systems of the type required
5 by the automotive industry.

The similarly conventional measure of multiple transmission of
the message on the same carrier, based on the hope that no
interference will occur throughout the entire transmission, in
10 many cases does not result in the required success,
particularly if the access control system has to be operated
in the vicinity of a continuously operating narrowband
interference source.

15 In a prior art method for carrying out simplex data
transmission disclosed in German Published, Non-Prosecuted
Patent Application DE 196 10 116 A1, a data message is
modulated onto two different carrier frequencies and
transmitted simultaneously in two different transmission
20 channels. In the receiver, the data messages from the two
transmission channels are combined into one single data
message.

25 In an unpublished further method for carrying out simplex data
transmission disclosed in International PCT document WO
00/20712 A1, a data message is modulated onto a plurality of

carrier frequencies and is transmitted simultaneously or in temporal succession in a plurality of transmission channels. In the receiver, the transmission channel and its data message in which the lowest signal-to-noise ratio is present are
5 selected.

Summary of the Invention:

It is accordingly an object of the invention to provide a method and device for carrying out simplex data transmission that overcomes the hereinafore-mentioned disadvantages of the heretofore-known devices and methods of this general type and that achieves a clear increase in reliability without a substantial increase in cost.

10
15
20
25
With the foregoing and other objects in view, there is provided, in accordance with the invention, a method for carrying out simplex transmission of a data message modulated onto a carrier frequency, including the steps of transmitting a data message more than one time using at least two different carrier frequencies in temporal succession to increase immunity to interference, and only changing the carrier frequencies such that the frequencies occur within one single transmission channel. Preferably, the method carries out simplex radio transmission in a radio access control system

The invention applies, in accordance with another mode of the invention, the fundamental concept of performing a multiple transmission of a data message that is to be transferred on at least two different carrier frequencies. The use of a
5 different carrier frequency for each of the transmissions is particularly efficient.

The proposed measure is surprisingly advantageous, particularly in the case of low-cost radio access control systems for motor vehicles because such systems already use low-cost components with high tolerances (for example, crystals and surface wave filters) and, thus, - due to cost rather than for technical reasons - have a relatively broadband configuration. Small deliberate changes to the carrier frequency can, therefore, easily be made in such systems with no significant effect on the transmission parameters, or can easily be incorporated in the construction of such systems with no substantial impact on cost.

20 The proposed method, which is referred to below as the Frequency Offset Re-Transmission ("FORT") method, generally offers advantages, even in its commonest form, if the receiver reveals a performance dependency on the carrier frequency or the carrier frequency/interference frequency ratio, which can
25 be derived even from statistical analysis, i.e., if the existence of an interference source is to be assumed beyond

the possible transmission duration, the source, of course, has a specific, more or less broad interference frequency spectrum, and the probability of a reduction in the interference rises with an increase in the effective increase in bandwidth of the user data signal transmission - achieved through multiple transmission at different frequencies.

Due to the tolerances, low-cost systems must have a more broadband construction than is actually necessary. As such, the receiver is able to process not only signals at the nominal carrier frequency, but also signals with slightly deviating carrier frequencies (typically ± 300 ppm) (\rightarrow receiver bandwidth).

The purpose of the change in the carrier frequency is to change the effect of the interference on the receiver, rather than to eliminate (narrowband) interference as in the case of multi-channel systems. To accomplish the change, the receiver performance must show a dependency on the carrier frequency/interference frequency ratio.

Such a dependency may be more or less significant in different receiver configurations or implementations. If the carrier frequency/interference frequency ratio within the permitted receiver bandwidth has a significant effect on performance, in particular, if minor frequency changes produce substantial

changes, the method according to the invention can be advantageously used. If, on the other hand, hardly any dependency can be identified, the method brings no improvements, but does not cause any disadvantages.

5 Accordingly, the method can be used ubiquitously without disadvantageous effects (apart from a minimal increase in implementation cost).

Thus, the improvement achieved by the method according to the invention includes a statistically verifiable higher rate of successful message transmissions.

In accordance with a further mode of the invention, the method is particularly advantageous in respect of narrowband interference in conjunction with the use of spread spectrum technology, in particular, in Direct Sequence Spread Spectrum ("DSSS") transmission.

From simulation calculations and general system observations,
20 it can be inferred that a frequency deviation between the different carrier frequencies used in a multiple transmission in the order of magnitude of the data rate, in particular, ranging from one quarter to two times the data rate, can be regarded as appropriate. Such differences are tolerated by
25 the systems concerned without significant parameter

modifications, and are adequate for a multiplicity of typical interference situations.

FIG. 2 graphically illustrates a special transmission function of a spread sequence. As is immediately evident from the existence of distinct maxima and minima on the curve, the transmission function acts on narrowband interference sources as a filter that either attenuates (minimum) or, in the unfavorable case, amplifies (maximum) the interference source. The gain that can essentially be achieved with the DSSS transmission is, therefore, depending on the position of the interference source, either increased or reduced, which, of course, has a direct effect on the signal-to-noise ratio and, therefore, the bit error rate.

If the transmission frequency is slightly modified with each new transmission of a data message, the carrier frequency control/synchronization circuit at the receiving end is also set to the modified frequency with the conversion of the receive signal into the baseband. However, because the interference signal - according to a practical assumption - does not change its frequency, it is "mapped" onto a different frequency with each new transmission by the conversion into the baseband. Because the transmission function of the spread sequence does not take effect until synchronization has taken place in the baseband, a different signal-to-noise ratio is

produced for each transmission. Again, statistical evidence indicates that, in the case of a plurality of transmissions, at least one has taken place in which a higher signal-to-noise ratio has been achieved than in the first transmission - and, therefore, in a conventional transmission without carrier frequency detuning.

As a result, in one variant of the invention with a receiver acknowledgement function, the transmission is carried out at different carrier frequencies until a data message with no bit errors is received at the receiving end. The multiple transmission could then be interrupted, which can help to reduce the response time of the access control system, which (as already explained above) is one of the most critical parameters for practical use. (In the case of simplex transmission, it is not possible to determine whether or not a message has been received without errors.)

In a further configuration of the invention, which can be used depending on the specific response of a synchronization circuit that is used, once synchronization has been achieved, an improvement in the effectiveness of the response is achieved by an additional, controlled frequency detuning that takes place without loss of synchronization, in cases where synchronization performance and bit error performance

(determined by the specific transmission function of the spread sequence) are intended to have a compensating effect.

The amount of the carrier frequency change does not need to be very precisely defined because its effect (as explained above) is statistically determined. Tolerances in the $\pm 10\%$ range can be regarded as permitted, and imply a substantial advantage for implementation in low-cost systems. The tolerance range can be within $\pm 1\%$ to 10% .

With the objects of the invention in view, there is also provided a device for carrying out simplex transmission of a data message modulated onto a carrier frequency, including a carrier frequency generator for generating different carrier frequencies, the carrier frequency generator having at least one capacitor and a detunable oscillator crystal detuned through the at least one capacitor, and a transmitter modulating data messages with the carrier frequencies and transmitting the data messages in temporal succession.

A very simple and low-cost option for implementing the different carrier frequencies entails the connection of at least one capacitor, preferably, a plurality of capacitors, with different capacitances and/or in different interconnections, to an oscillator crystal of the carrier

frequency generator, which is detuned in a specific manner by the capacitor(s).

In accordance with an added mode of the invention, the at

5 least one capacitor is a plurality of capacitors and a switch respectively connects at least one of the plurality of capacitors to the oscillator crystal to generate different carrier frequencies.

10 In accordance with an additional feature of the invention, the switch is a program-controlled switch.

15 In accordance with yet another feature of the invention, there is provided a carrier frequency control device for setting different carrier frequencies in a case of multiple transmission, the control device connected to at least one of the group consisting of the plurality of capacitors and the switch.

20 With the objects of the invention in view, there is also provided a device for carrying out simplex transmission of a data message modulated onto a carrier frequency, including a carrier frequency generator for generating different carrier frequencies, the carrier frequency generator having at least
25 one capacitor and a detunable oscillator crystal detuned through the at least one capacitor, and a transmitter

modulating data messages with the carrier frequencies and transmitting the data messages more than one time using at least two different carrier frequencies in temporal succession to increase immunity to interference; the carrier frequencies
5 only changed to have the carrier frequencies occur within one single transmission channel.

Other features that are considered as characteristic for the invention are set forth in the appended claims.

10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995
1000
1005
1010
1015
1020
1025
1030
1035
1040
1045
1050
1055
1060
1065
1070
1075
1080
1085
1090
1095
1100
1105
1110
1115
1120
1125
1130
1135
1140
1145
1150
1155
1160
1165
1170
1175
1180
1185
1190
1195
1200
1205
1210
1215
1220
1225
1230
1235
1240
1245
1250
1255
1260
1265
1270
1275
1280
1285
1290
1295
1300
1305
1310
1315
1320
1325
1330
1335
1340
1345
1350
1355
1360
1365
1370
1375
1380
1385
1390
1395
1400
1405
1410
1415
1420
1425
1430
1435
1440
1445
1450
1455
1460
1465
1470
1475
1480
1485
1490
1495
1500
1505
1510
1515
1520
1525
1530
1535
1540
1545
1550
1555
1560
1565
1570
1575
1580
1585
1590
1595
1600
1605
1610
1615
1620
1625
1630
1635
1640
1645
1650
1655
1660
1665
1670
1675
1680
1685
1690
1695
1700
1705
1710
1715
1720
1725
1730
1735
1740
1745
1750
1755
1760
1765
1770
1775
1780
1785
1790
1795
1800
1805
1810
1815
1820
1825
1830
1835
1840
1845
1850
1855
1860
1865
1870
1875
1880
1885
1890
1895
1900
1905
1910
1915
1920
1925
1930
1935
1940
1945
1950
1955
1960
1965
1970
1975
1980
1985
1990
1995
2000
2005
2010
2015
2020
2025
2030
2035
2040
2045
2050
2055
2060
2065
2070
2075
2080
2085
2090
2095
2100
2105
2110
2115
2120
2125
2130
2135
2140
2145
2150
2155
2160
2165
2170
2175
2180
2185
2190
2195
2200
2205
2210
2215
2220
2225
2230
2235
2240
2245
2250
2255
2260
2265
2270
2275
2280
2285
2290
2295
2300
2305
2310
2315
2320
2325
2330
2335
2340
2345
2350
2355
2360
2365
2370
2375
2380
2385
2390
2395
2400
2405
2410
2415
2420
2425
2430
2435
2440
2445
2450
2455
2460
2465
2470
2475
2480
2485
2490
2495
2500
2505
2510
2515
2520
2525
2530
2535
2540
2545
2550
2555
2560
2565
2570
2575
2580
2585
2590
2595
2600
2605
2610
2615
2620
2625
2630
2635
2640
2645
2650
2655
2660
2665
2670
2675
2680
2685
2690
2695
2700
2705
2710
2715
2720
2725
2730
2735
2740
2745
2750
2755
2760
2765
2770
2775
2780
2785
2790
2795
2800
2805
2810
2815
2820
2825
2830
2835
2840
2845
2850
2855
2860
2865
2870
2875
2880
2885
2890
2895
2900
2905
2910
2915
2920
2925
2930
2935
2940
2945
2950
2955
2960
2965
2970
2975
2980
2985
2990
2995
3000
3005
3010
3015
3020
3025
3030
3035
3040
3045
3050
3055
3060
3065
3070
3075
3080
3085
3090
3095
3100
3105
3110
3115
3120
3125
3130
3135
3140
3145
3150
3155
3160
3165
3170
3175
3180
3185
3190
3195
3200
3205
3210
3215
3220
3225
3230
3235
3240
3245
3250
3255
3260
3265
3270
3275
3280
3285
3290
3295
3300
3305
3310
3315
3320
3325
3330
3335
3340
3345
3350
3355
3360
3365
3370
3375
3380
3385
3390
3395
3400
3405
3410
3415
3420
3425
3430
3435
3440
3445
3450
3455
3460
3465
3470
3475
3480
3485
3490
3495
3500
3505
3510
3515
3520
3525
3530
3535
3540
3545
3550
3555
3560
3565
3570
3575
3580
3585
3590
3595
3600
3605
3610
3615
3620
3625
3630
3635
3640
3645
3650
3655
3660
3665
3670
3675
3680
3685
3690
3695
3700
3705
3710
3715
3720
3725
3730
3735
3740
3745
3750
3755
3760
3765
3770
3775
3780
3785
3790
3795
3800
3805
3810
3815
3820
3825
3830
3835
3840
3845
3850
3855
3860
3865
3870
3875
3880
3885
3890
3895
3900
3905
3910
3915
3920
3925
3930
3935
3940
3945
3950
3955
3960
3965
3970
3975
3980
3985
3990
3995
4000
4005
4010
4015
4020
4025
4030
4035
4040
4045
4050
4055
4060
4065
4070
4075
4080
4085
4090
4095
4100
4105
4110
4115
4120
4125
4130
4135
4140
4145
4150
4155
4160
4165
4170
4175
4180
4185
4190
4195
4200
4205
4210
4215
4220
4225
4230
4235
4240
4245
4250
4255
4260
4265
4270
4275
4280
4285
4290
4295
4300
4305
4310
4315
4320
4325
4330
4335
4340
4345
4350
4355
4360
4365
4370
4375
4380
4385
4390
4395
4400
4405
4410
4415
4420
4425
4430
4435
4440
4445
4450
4455
4460
4465
4470
4475
4480
4485
4490
4495
4500
4505
4510
4515
4520
4525
4530
4535
4540
4545
4550
4555
4560
4565
4570
4575
4580
4585
4590
4595
4600
4605
4610
4615
4620
4625
4630
4635
4640
4645
4650
4655
4660
4665
4670
4675
4680
4685
4690
4695
4700
4705
4710
4715
4720
4725
4730
4735
4740
4745
4750
4755
4760
4765
4770
4775
4780
4785
4790
4795
4800
4805
4810
4815
4820
4825
4830
4835
4840
4845
4850
4855
4860
4865
4870
4875
4880
4885
4890
4895
4900
4905
4910
4915
4920
4925
4930
4935
4940
4945
4950
4955
4960
4965
4970
4975
4980
4985
4990
4995
5000
5005
5010
5015
5020
5025
5030
5035
5040
5045
5050
5055
5060
5065
5070
5075
5080
5085
5090
5095
5100
5105
5110
5115
5120
5125
5130
5135
5140
5145
5150
5155
5160
5165
5170
5175
5180
5185
5190
5195
5200
5205
5210
5215
5220
5225
5230
5235
5240
5245
5250
5255
5260
5265
5270
5275
5280
5285
5290
5295
5300
5305
5310
5315
5320
5325
5330
5335
5340
5345
5350
5355
5360
5365
5370
5375
5380
5385
5390
5395
5400
5405
5410
5415
5420
5425
5430
5435
5440
5445
5450
5455
5460
5465
5470
5475
5480
5485
5490
5495
5500
5505
5510
5515
5520
5525
5530
5535
5540
5545
5550
5555
5560
5565
5570
5575
5580
5585
5590
5595
5600
5605
5610
5615
5620
5625
5630
5635
5640
5645
5650
5655
5660
5665
5670
5675
5680
5685
5690
5695
5700
5705
5710
5715
5720
5725
5730
5735
5740
5745
5750
5755
5760
5765
5770
5775
5780
5785
5790
5795
5800
5805
5810
5815
5820
5825
5830
5835
5840
5845
5850
5855
5860
5865
5870
5875
5880
5885
5890
5895
5900
5905
5910
5915
5920
5925
5930
5935
5940
5945
5950
5955
5960
5965
5970
5975
5980
5985
5990
5995
6000
6005
6010
6015
6020
6025
6030
6035
6040
6045
6050
6055
6060
6065
6070
6075
6080
6085
6090
6095
6100
6105
6110
6115
6120
6125
6130
6135
6140
6145
6150
6155
6160
6165
6170
6175
6180
6185
6190
6195
6200
6205
6210
6215
6220
6225
6230
6235
6240
6245
6250
6255
6260
6265
6270
6275
6280
6285
6290
6295
6300
6305
6310
6315
6320
6325
6330
6335
6340
6345
6350
6355
6360
6365
6370
6375
6380
6385
6390
6395
6400
6405
6410
6415
6420
6425
6430
6435
6440
6445
6450
6455
6460
6465
6470
6475
6480
6485
6490
6495
6500
6505
6510
6515
6520
6525
6530
6535
6540
6545
6550
6555
6560
6565
6570
6575
6580
6585
6590
6595
6600
6605
6610
6615
6620
6625
6630
6635
6640
6645
6650
6655
6660
6665
6670
6675
6680
6685
6690
6695
6700
6705
6710
6715
6720
6725
6730
6735
6740
6745
6750
6755
6760
6765
6770
6775
6780
6785
6790
6795
6800
6805
6810
6815
6820
6825
6830
6835
6840
6845
6850
6855
6860
6865
6870
6875
6880
6885
6890
6895
6900
6905
6910
6915
6920
6925
6930
6935
6940
6945
6950
6955
6960
6965
6970
6975
6980
6985
6990
6995
7000
7005
7010
7015
7020
7025
7030
7035
7040
7045
7050
7055
7060
7065
7070
7075
7080
7085
7090
7095
7100
7105
7110
7115
7120
7125
7130
7135
7140
7145
7150
7155
7160
7165
7170
7175
7180
7185
7190
7195
7200
7205
7210
7215
7220
7225
7230
7235
7240
7245
7250
7255
7260
7265
7270
7275
7280
7285
7290
7295
7300
7305
7310
7315
7320
7325
7330
7335
7340
7345
7350
7355
7360
7365
7370
7375
7380
7385
7390
7395
7400
7405
7410
7415
7420
7425
7430
7435
7440
7445
7450
7455
7460
7465
7470
7475
7480
7485
7490
7495
7500
7505
7510
7515
7520
7525
7530
7535
7540
7545
7550
7555
7560
7565
7570
7575
7580
7585
7590
7595
7600
7605
7610
7615
7620
7625
7630
7635
7640
7645
7650
7655
7660
7665
7670
7675
7680
7685
7690
7695
7700
7705
7710
7715
7720
7725
7730
7735
7740
7745
7750
7755
7760
7765
7770
7775
7780
7785
7790
7795
7800
7805
7810
7815
7820
7825
7830
7835
7840
7845
7850
7855
7860
7865
7870
7875
7880
7885
7890
7895
7900
7905
7910
7915
7920
7925
7930
7935
7940
7945
7950
7955
7960
7965
7970
7975
7980
7985
7990
7995
8000
8005
8010
8015
8020
8025
8030
8035
8040
8045
8050
8055
8060
8065
8070
8075
8080
8085
8090
8095
8100
8105
8110
8115
8120
8125
8130
8135
8140
8145
8150
8155
8160
8165
8170
8175
8180
8185
8190
8195
8200
8205
8210
8215
8220
8225
8230
8235
8240
8245
8250
8255
8260
8265
8270
8275
8280
8285
8290
8295
8300
8305
8310
8315
8320
8325
8330
8335
8340
8345
8350
8355
8360
8365
8370
8375
8380
8385
8390
8395
8400
8405
8410
8415
8420
8425
8430
8435
8440
8445
8450
8455
8460
8465
8470
8475
8480
8485
8490
8495
8500
8505
8510
8515
8520
8525
8530
8535
8540
8545
8550
8555
8560
8565
8570
8575
8580
8585
8590
8595
8600
8605
8610
8615
8620
8625
8630
8635
8640
8645
8650
8655
8660
8665
8670
8675
8680
8685
8690
8695
8700
8705
8710
8715
8720
8725
8730
8735
8740
8745
8750
8755
8760
8765
8770
8775
8780
8785
8790
8795
8800
8805
8810
8815
8820
8825
8830
8835
8840
8845
8850
8855
8860
8865
8870
8875
8880
8885
8890
8895
8900
8905
8910
8915
8920
8925
8930
8935
8940
8945
8950
8955
8960
8965
8970
8975
8980
8985
8990
8995
9000
9005
9010
9015
9020
9025
9030
9035
9040
9045
9050
9055
9060
9065
9070
9075
9080
9085
9090
9095
9100
9105
9110
9115
9120
9125
9130
9135
9140
9145
9150
9155
9160
9165
9170
9175
9180
9185
9190
9195
9200
9205
9210
9215
9220
9225
9230
9235
9240
9245
9250
9255
9260
9265
9270
9275
9280
9285
9290
9295
9300
9305
9310
9315
9320
9325
9330
9335
9340
9345
9350
9355
9360
9365
9370
9375
9380
9385
9390
9395
9400
9405
9410
9415
9420
9425
9430
9435
9440
9445
9450
9455
9460
9465
9470
9475
9480
9485
9490
9495
9500
9505
9510
9515
9520
9525
9530
9535
9540
9545
9550
9555
9560
9565
9570
9575
9580
9585
9590
9595
9600
9605
9610
9615
9620
9625
9630
9635
9640
9645
9650
9655
9660
9665
9670
9675
9680
9685
9690
9695
9700
9705
9710
9715
9720
9725
9730
9735
9740
9745
9750
9755
9760
9765
9770
9775
9780
9785
9790
9795
9800
9805
9810
9815
9820
9825
9830
9835
9840
9845
9850
9855
9860
9865
9870
9875
9880
9885
9890
9895
9900
9905
9910
9915
9920
9925
9930
9935
9940
9945
9950
9955
9960
9965
9970
9975
9980
9985
9990
9995
10000
10005
10010
10015
10020
10025
10030
10035
10040
10045
10050
10055
10060
10065
10070
10075
10080
10085
10090
10095
10100
10105
10110
10115
10120
10125
10130
10135
10140
10145
10150
10155
10160
10165
10170
10175
10180
10185
10190
10195
10200
10205
10210
10215
10220
10225
10230
10235
10240
10245
10250
10255
10260
10265
10270
10275
10280
10285
10290
1

FIG. 1 is a block and schematic circuit diagram of a device for carrying out the method according to the invention;

FIG. 2 is a graph of a specific transmission function of a DSSS transmission according to the invention; and

FIGS. 3 to 6 are each graphs illustrating simulation results showing the increase in transmission quality of the application of the method according to the invention.

Description of the Preferred Embodiments:

Referring now to the figures of the drawings in detail and first, particularly to FIG. 1 thereof, there is shown a basic diagram illustrating a simple configuration of a detunable carrier frequency generator G. In the generator G, a conventional oscillator crystal Q is optionally connected through one of three capacitors C1, C2, C3 with different capacitances to ground (GND) and the oscillation frequency of the oscillator circuit O is influenced by the respective connected capacitor. The oscillator circuit O supplies a reference frequency f_R for a PLL circuit PLL, which - in a conventional manner - has a phase discriminator PD, a low-pass filter LP, a voltage-controlled oscillator VCO and an :N- divider D in the conventional circuit, and at whose output the carrier frequency f_C is provided as an N-fold of the reference frequency f_R . The capacitors C1, C2, C3 are connected by a

carrier frequency control unit FC in accordance with a predefined routine (for example, stored in an internal program memory of the frequency control unit). The capacitances of the capacitors are selected so that the (otherwise
5 conventionally constructed) oscillator O is detuned such that the resulting change in the carrier frequency lies in the order of magnitude of the data rate. The time characteristic of the carrier frequency variation is limited, on one hand, by the scope of the data message and the transmission rate and, on the other hand, by the required response time of the system, so that several tens of milliseconds are typically required for each transmission procedure (according to the current state of knowledge) and a number of between two and around ten transmissions are possible.

FIG. 2 shows a transmission function of a spread sequence used for DSSS transmission according to a further development of the method according to the invention. The f/f_{chip} ratio is plotted on the X-axis and the transmission gain is plotted on
20 the Y-axis. As already mentioned above, the transmission function shows that the method of the invention, in conjunction with the use of DS spread spectrum technology, for statistical reasons produces a gain in transmission quality. Specifically, three randomly selected carrier frequencies F1, F2 and F3 are included in the graphical representation. Gain
25 values of around -2 dB, 0 and +1 dB correspond to these

frequencies. Thus, for any given output carrier frequency (here, for example, F_2), there exists a probability, which increases with the number of variation steps, of achieving a more favorable signal-to-noise ratio than at the outset, with at least one variation step in relation to a narrowband interference source.

FIGS. 3 to 6 illustrate contrasting simulation results to compare a conventional data message transmission on a constant carrier frequency with a transmission using a varied carrier frequency ("FORT"). The difference between the initial signal-to-noise ratio S/N and the process gain G_p achieved through the use of spread spectrum technology (with a spread factor 31 around 15 dB) is plotted on the X-axis and the probability of a successful transmission is plotted as a percentage on the Y-axis.

The following assumptions have been made in determining the results:

A very narrowband, random-frequency interference is present.

The synchronization has no effect on performance.

The initial S/N ratio (S/N) is modified by the value of the spread sequence transmission function at the interference frequency (mapped onto the baseband). As a result, for the simulation, any given transmission function value was selected for each pass.

The bit error rate is derived from the bit error curve for PSK (Phase Shift keying) through the AWGN channel.

The change in the carrier frequency in the case of FORT is subject to certain randomness due to tolerances of the components.

A transmission attempt is deemed to be successful if at least one message contained no bit error.

The following FORT transmission parameters were selected or varied:

Message length "I" (number of bits): 128 and 32;

Frequency change "foffset", related to data rate (data rate = $1/31$ * chip frequency fchip): $0.5 \cdot \text{data rate}$ and $0.75 \cdot \text{data rate}$;

Tolerance of the frequency change "tol": 10% (\rightarrow e.g.
foffset = $0.45 \dots 0.55 \cdot \text{data rate}$); and

Number of the telegram repetition "repeat": 2 and 3.

5

It is evident that, particularly in the high reliability range (successful transmission attempts $> 95\%$), use of the FORT method brings advantages. Here, the gain in the initial S/N ratio is 2 dB and more.

Implementation of the invention is not restricted to the examples illustrated above, but is also possible in a multiplicity of variations. Thus, in particular, further options exist for controlled variation of the carrier frequency and further options for combination of the proposed method with spread spectrum technologies and advanced modulation and coding methods. Essentially, the method can also be advantageously used in duplex data transmissions.